Item no.: 2060750



Presence and motion detectors Wall installation indoor

Description

- Passive infra-red motion detector for wall installation
- Square detection area 170°, 14 x 17 m (238 m²)
- Without frame, adapter frames for common switch ranges available as accessory
- 1 channel light
- Fully or semi-automatic operation
- Adjustable brightness switching value, teach-in function
- Staircase light function
- Switch-on delay configurable
- Extension of detection area via master/slave switching
- Ready for immediate use due to factory presetting
- Restriction of detection area possible
- Mixed light measurement suitable for the control of fluorescent, incandescent, halogen lamps and LEDs
- Integrated button (can be blocked)
- Product design by ID AID



Technical data


	theMura S180-100 B UP	
Operating voltage	230 V AC	
Frequency	50 - 60 Hz	
Installation height	0.8 - 1.2 m	
Installation type	Flush-mounted wall installation	
Colour	White	
Switching output	Light	
Power consumption	~0.4 W	
Light measurement	Mixed light measurement	
Setting range brightness	5 - 1000 lx	
Light switch-off delay	Impuls, 10 s - 30 min	
Lamp types	Incandescent/halogen lamps, fluorescent lamps, Energy saving lamps, LEDs	

	theMura S180-100 B UP		
Incandescent/halogen lamp load	escent/halogen lamp load 2300 W		
Inrush current	max. 600 A / 200 µs		
LED lamp < 2 W	40 W		
LED lamp 2-8 W	450 W		
LED lamp > 8 W	450 W		
Type of connection	Spring terminals		
Size of concealed housing	55 mm		
Detection range	238 m² (14 x 17 m)		
Detection angle	170°		
Ambient temperature	-15°C 45°C		
Type of protection	IP 20		

Item no.: 2060750





Connection example



Detection range for planning applications at a temperature of 21 °C

Mounting height (A)	Head on to (R)	Diagonally (t)	Sitting (S)
1.2 m	120 m² 12 m x 10 m	238 m² 14 m x 17 m	







Item no.: 2060750




Scale drawings


theMura S180-100 UP WH (2060650) + theMura S180-101 UP WH (2060655)








theMura S180-100 UP (2060750) + theMura S180-101 B UP (2060755)





Accessories

Surface frame LUXA 103-200 Item no.: 9070504



Adapter frame 45A BJBSI WH Item no.: 9070788



Adapter frame 45A MMP WH Item no.: 9070790



Adapter frame 45A GS WH Item no.: 9070791



Item no.: 2060750



Accessories

Adapter frame 45A JAS WH Item no.: 9070789




Cover frame theMura LM WH Item no.: 9070787



Adapter frame 45A BS WH

Item no.: 9070792

Adapter frame 45A BJRE WH Item no.: 9070754



Cover frame the Mura Theben WH

Item no.: 9070798

Adapter frame 45A MEMP CL Item no.: 9080004



Cover frame theMura FED WH

Item no.: 9070786

Adapter frame 45A GIST CL Item no.: 9080005



Adapter frame 45A BESI CL Item no.: 9080006



Adapter frame 45A BJBA CL Item no.: 9080002



Adapter frame 45A JUAS CL Item no.: 9080003



Adapter frame 45A BJRE CL Item no.: 9080001







Item no.: 2060750



Accessories

Adapter frame 45A FEED CL Item no.: 9080007

